

GSM communicator G16

Communicator G16 is intended to upgrade compatible intruder alarm panels for event signalling via cellular network.

Communicator transmits full event information to Alarm Receiving Centre.

Customers are informed about security system events in Protegus apps or with SMS messages. They can Arm/Disarm the alarm system remotely (via panel's keyswitch zone or directly via Serial port for Paradox panels).

Communicator features

Connection

- Connection to control panels via:
 - Keypad data bus; or
 - Serial port

Communications

- Two main communication channels working simultaneously
- Each channel has a separate back-up channel
- Connection control with ARC
- Simultaneous event reporting to Protegus Mobile/Web application, allowing user to remotely monitor and control its alarm system
- Event messages are transmitted in Contact ID codes
- Event reporting via SMS messages to four different users in user-friendly SMS messages
- Remote Arm/Disarm feature with Paradox

Configuration

- Quick and easy installation
- Remote configuration and firmware updates
- Two access levels for setting of operating parameters



Inputs and outputs

- 2 Outputs controlled via:
 - Mobile/Web application or
 - SMS
- 1 selectable type input: NC or NO



Technical Parameters

| | |
|-------------------------|---|
| GSM modem frequencies | 850 / 900 / 1800 / 1900 MHz |
| UTMS modem frequencies | 800 / 850 / 900 / 1900 / 2100 MHz |
| Power supply | DC 10-18V |
| Current consumption | 60-100 mA (on standby) Up to 250 mA (while sending data) |
| Transmission protocols | TRK, DC-09_2007, DC-09_2012 |
| Message encryption | AES 128 |
| Memory | Up to 60 messages |
| Inputs | 1, NC/NO type |
| Output | 2 x OC type, commutating up to 0,15 A DC, 30 V max |
| Parameter configuration | Locally via USB port or remotely |
| Operating environment | Temperature from -10 °C to 50 °C, relative humidity – up to 80% at +20 °C |
| Communicator dimensions | 65 x 77 x 25 mm |

List of Compatible Control Panels

| | |
|-----------------|---|
| DSC® | PC1404, PC1565, PC5020, PC1616, PC1832, PC1864 |
| | SPECTRA SP4000, SP5500, SP6000, SP7000, 1727, 1728, 1738 |
| PARADOX® | MAGELLAN MG5000, MG5050 |
| | DIGIPLEX EVO192 |
| | Esprit series: E55, 728ULT, 738ULT |
| UTC Interlogix® | NetworX (Caddx) NX-4v2, NX-6v2, NX-8v2, NX-8e |
| Texecom® | Premier 412, 816, 816+, 832 Premier Elite 12, 24, 48, 88, 168, 640 |